



Product Image





MARKETING INFORMATION AND CLAIMS

Product Description

The Panel Work Light has a variety of features that make this light very versatile. Its 2 adjustable panels provide 180° of lighting (each) and you can direct the light wherever you need. In addition to that, both legs are adjustable so you can place it however you need and also hang it anywhere. This light is not only rechargeable but it also has a USB port out which can be used to charge other devices. This USB port feature may come in handy in emergency situations. No matter the activity, be it work, DIY project, outdoors or camping, the Panel Work Light is a great option for your lighting needs.

DESIGN FEATURES AND BENEFITS

- ✓ Durable construction for tough situations
- ✓ Adjustable handle that can be used to position the light or hang it
- ✓ 2 Adjustable panels (180 lighting each)
- ✓ Rechargeable (cable included)
- ✓ USB Port Out to charge other devices
- ✓ Panels adjust individually for maximum flexibility
- ✓ 4x Green Color LED charging indicator for 25, 50, 75, 100% charge

PERFORMANCE FEATURES AND BENEFITS

- ✓ Powerful bright light
- ✓ 2 panels that provide 180 degrees of lighting
- ✓ Features LED Technology
- ✓ Operates on 4900mAh Li-ion Rechargeable battery



OPERATION

Modes and Features

High Spot	X	High Flood (Wide)	Warm Mode	Red	Area High
Medium Spot		Medium Flood (Wide)	Cool Mode	Red Flashing	Area Medium
Low Spot	X	Low Flood (Wide)	Warm and Cool Together	Green	Area Low
Ultra Low Spot		Emergency Strobe (>5hz see warning copy)		Green Flashing	Nightlight
Press and Hold Dimming		Safety Flashing <5Hz		SOS	

OPERATING INSTRUCTIONS

- Press 1 time for high.
- Press 2 times for half panel light (low).
- Press 3 times for other half panel (low).

BATTERY CHANGING or CHARGING INSTRUCTIONS

- Battery is not user replaceable.
- To charge use included USB cord and plug light into any USB charging port.
- Light may be used while charging but charging time will be increased. For best charging performance, charge with light turned off.
- Charging Indicator light is located near charging port.

BATTERY CHARGE INDICATOR

- Charge indicating LEDs are located by the USB port. They will illuminate when the USB charging has started.
While charging:
 - 1 LED blinking---0-25%
 - 2 LEDs blinking---26-50%
 - 3 LEDs blinking---51-75%
 - 4 LEDs blinking---76-99%
 - 4 LEDs solid ON ---Fully charged--- 100%

Energizer Panel Work Light

AWLL8



ENGINEERING DATA

ANSI PERFORMANCE DATA

Lumens	Runtime	Beam Distance	Drop	Water Ingress
FL1 STANDARD 1100 LUMENS	FL1 STANDARD 6h	FL1 STANDARD 46m	FL1 STANDARD 2m	FL1 STANDARD IPX4

BATTERY PERFORMANCE

Battery Type	Lithium Ion		
Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
High	1100	6	46
Low	550	12	-

PRODUCT SPECIFICATIONS

Weight:	462	grams	16.3	ounces	
Dimensions:	Length		Width		Height
	202	mm	49	mm	147
	8	in	1.9	in	5.8
Weight does not include user replaceable batteries (unless specified)					

BATTERY SPECIFICATIONS

Quantity:	2	Size:	18650	User Replaceable?	No
Type:	Rechargeable Lithium Ion				

ELECTRICAL CHARACTERISTICS

Nominal Power Consumption:	8.7 W		
Batteries:	2 Li ion 4900mAh 18650 3.7V dc		
LED Specifications:	LED 3.0V cc / 2900 mA		
Rechargeable Input Voltage:	5V 0.7A	Output Voltage:	-
Time to Charge	8 hours		

Contains magnets?	Shatterproof Lens:
No	No
LED CCT	LED CRI
5000K	80
Additional Ingress Protection	Other (Impact Testing, etc)
-	-



Regulatory Information

CERTIFICATES AND COMPLIANCE

Global Certifications

X	EMC EN62471	Global
X	FCC	Tested on all product globally required for USA only.
	ASTM F963 Ages 3+	Global- All products marketed to children

Regional Certifications

	RCM	Australia-Rechargeable products		NOM	Mexico—All Lights		CNS	Taiwan-All rechargeable products
	EAC	EU-Rechargeable products		InMetro	Brazil-AC Plug In Rechargeable		KC Mark	South Korea-All rechargeable products
				UL/S Mark	Argentina-AC Plug In Rechargeable			
				Triman Logo	France—All lights			



REQUIRED REGULATORY INFO

Tested according to ANSI FL1 Standards.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

PRODUCT WARNINGS and/or DISCLAIMERS