



The *Energizer*® Vision HD Compact light delivers high-performance innovation in a convenient size. Designed to fit in your vehicle, pocket or bag, the *Energizer* Vision HD Compact is perfect for a wide variety of tasks. Unique MAXVIZ technology delivers a wide, powerful beam that provides users sharp, high-definition vision. A smooth, digital switch provides access to multiple beam settings: high, power saver and emergency strobe modes. Featuring an advanced alloy construction, the *Energizer* Vision HD is a durable solution that delivers powerful daylight-color illumination at home or on-the-go.

Lumens	Runtime	Beam Distance	Drop	Water Ingress
<p>FL1 STANDARD 270 LUMENS</p>	<p>FL1 STANDARD 2h 30m</p>	<p>FL1 STANDARD 84m</p>	<p>FL1 STANDARD 1m</p>	<p>FL1 STANDARD IPX4</p>

- ### DESIGN BENEFITS
- ✓ Durable aircraft grade aluminum construction
 - ✓ Smooth digital switch to allow easy access to light modes
 - ✓ Hold the switch for two seconds to activate strobe mode
 - ✓ Easily replaceable batteries
 - ✓ Shatterproof lens

- ### PERFORMANCE BENEFITS
- ✓ MAXVIZ Technology to deliver a wide, powerful beam and high-definition vision
 - ✓ Up to 12X Brighter than Standard LED Technology
 - ✓ Extended Run Time

- ### LIGHT AND POWER SOURCE
- ✓ Features LED Technology
 - ✓ 4.25hz strobe light
 - ✓ Operates on 3 AAA batteries

PRODUCT SPECIFICATIONS

Weight:	84 Grams / 2.97 Ounces
Dimensions:	98 mm x 34 mm x 34 mm 3.86" x 1.34" x 1.34"

ELECTRICAL CHARACTERISTICS

Nominal Power Consumption:	2.7 W
Batteries:	3 AAA Energizer E92 4.5V dc
LED Specifications:	LED 3.0V cc / 900 mA

DISCLAIMERS

Tested according to ANSI FL1 Standards.
 This device complies with part 15 of the FCC Rules.
 Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

CERTIFICATES AND COMPLIANCE

EMC, EN62471, FCC	
-------------------	--

Publish Date: 08-06-2022



BATTERY SPECIFICATIONS

Battery Type	Energizer Max Alkaline		
Battery Size	AAA		
Number of Cells	3		

BATTERY PERFORMANCE

Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
High	270	2:30	84
Low	80	12:30	45
Strobe	-	-	-

Modes

High, Low, Strobe

OPERATING INSTRUCTIONS

1. Press on/off button to turn on.
2. Press 1X for High.
3. Press 2X for Low.
4. Press 3X for Strobe.

BATTERY CHANGING INSTRUCTIONS

1. Batteries (3X AAA) are user replaceable.
2. Take out cartridge from flashlight. Insert batteries (-) towards the springs. Reinsert cartridge into flashlight according to the orientation the cartridge shows with an arrow.