



For the most demanding tasks, look no further than the *Energizer*® *HARDCASE*® *PROFESSIONAL*® *PIVOTPLUS*. With tool-quality construction and advanced LED technology, this light is designed to meet even the most challenging jobs. Constructed with Professionals in mind, it withstands drop after drop, off a ladder or even a two-story building. Designed with a 175 degrees pivoting function plus a versatile magnetic base, this light provides the flexibility needed for any project. The large push button switch can be easily operated while wearing gloves, while adjustable light modes let the user decide the balance of brightness and runtime. In addition, this light is water resistant for those rainy, outdoor tasks.

Lumens	Runtime	Beam Distance	Drop	Water Ingress



Automotive

DESIGN BENEFITS
<ul style="list-style-type: none"> <li>✓ Pivoting head rotates up to 175 degrees</li> <li>✓ Exceptionally durable</li> <li>✓ Survives drop after drop from a two-story building</li> <li>✓ Weather-resistant</li> <li>✓ Built-in lanyard slot</li> <li>✓ Large switch for easy operation</li> <li>✓ Shatterproof</li> </ul>

PERFORMANCE BENEFITS
<ul style="list-style-type: none"> <li>✓ Bright, uniform beam is ideal for projects</li> <li>✓ Adjustable beam output for extended runtime</li> <li>✓ Dimmable – Press and hold to select output</li> <li>✓ Magnetic base to secure light on metal surfaces</li> </ul>

LIGHT AND POWER SOURCE
<ul style="list-style-type: none"> <li>✓ Features Advanced LED Technology</li> <li>✓ Operates on 2 AA batteries</li> <li>✓ CCT 5000 CRI 70</li> </ul>

BATTERY SPECIFICATIONS	
Battery Type	Energizer Max Alkaline
Battery Size	AA
Number of Cells	2

PRODUCT SPECIFICATIONS	
Weight:	140 Grams / 4.9 Ounces
Dimensions:	180 mm x 50 mm x 45 mm 7" x 2" x 1.8"

BATTERY PERFORMANCE			
Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
High	300	5	30
Low	30	30	10

ELECTRICAL CHARACTERISTICS	
Nominal Power Consumption:	3.3 W
Batteries:	2 AA Energizer E91 3.0V dc
LED Specifications:	LED 3.0V cc / 110 mA

Modes
High, Low

DISCLAIMERS
<p>Tested according to ANSI FL1 Standards.</p> <p>This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.</p>

CERTIFICATES AND COMPLIANCE
EMC, EN62471, FCC

Publish Date: 08-06-2022

## OPERATING INSTRUCTIONS

1. Press on/off button to turn on.
2. Press 1X for High.
3. Press 2X for Low.
4. Hold to dim light gradually.

## BATTERY CHANGING INSTRUCTIONS

1. Batteries (2X AA) are user replaceable.
2. Unscrew tail cap and remove battery cartridge. Insert batteries into the cartridge with (+) end going in first. Re-screw tail cap onto flashlight.