



The *Energizer*® TAC 1000 delivers high performance in a durable and reliable construction. The rear push button, emergency strobe mode, and durable aircraft grade aluminum were designed to make this a great choice in various situations. It's rugged construction and high light output are perfect for DIY projects and other indoor needs but also makes it a great fit for outdoor activities, such as camping. Its powerful brightness and emergency strobe help you to stay protected in emergency situations.

Lumens	Runtime	Beam Distance	Drop	Water Ingress
<p>FL1 STANDARD 1000 LUMENS</p>	<p>FL1 STANDARD 4h</p>	<p>FL1 STANDARD 200m</p>	<p>FL1 STANDARD 1m</p>	<p>FL1 STANDARD 1m IPX7</p>



WARNING
A small percentage of people may experience a seizure when exposed to certain visual images, including flashing lights and strobing lights.

DESIGN BENEFITS
<ul style="list-style-type: none"> ✓ Rear push button to easily change modes while holding the light ✓ Rugged construction made of Durable aircraft grade aluminum ✓ Shatterproof lens ✓ Versatility: various modes

PERFORMANCE BENEFITS
<ul style="list-style-type: none"> ✓ Up to 15X brighter than standard LED technology ✓ Extended run time ✓ Emergency strobe mode

LIGHT AND POWER SOURCE
<ul style="list-style-type: none"> ✓ Features LED Technology ✓ Operates on 6 AA Batteries ✓ Emergency strobe: ~17 Hz frequency

PRODUCT SPECIFICATIONS
Weight: 340 Grams / 12 Ounces
Dimensions: 230 mm x 50 mm x 50 mm 9.1" x 2.0" x 2.0"

ELECTRICAL CHARACTERISTICS
Nominal Power Consumption: 10.8 W
Batteries: 6 AA Energizer E91 4.5V dc
LED Specifications: LED 3.0V cc / 3600 mA

DISCLAIMERS
<p>Tested according to ANSI FL1 Standards.</p> <p>This device complies with part 15 of the FCC Rules.</p> <p>Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.</p>

CERTIFICATES AND COMPLIANCE
EMC, EN62471, FCC

BATTERY SPECIFICATIONS	
Battery Type	Energizer Max Alkaline
Battery Size	AA
Number of Cells	6

BATTERY PERFORMANCE			
Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
High	1000	4	200
Low	250	15	-
Strobe	-	-	-

Modes
High, Low, Strobe

Publish Date: 09-06-2022

OPERATING INSTRUCTIONS

1. Press on/off button to turn on.
2. Press 1X for High.
3. Press 2X for Low.
4. Hold button for 2 seconds for Strobe.

BATTERY CHANGING INSTRUCTIONS

1. Batteries (6X AAA) are user replaceable.
2. Unscrew tail cap and insert batteries into the flashlight with (+) end going in first. Re-screw tail cap onto the flashlight.