



The *Energizer* Vision HD+ Focus headlamp is another innovative headlamp solution within the *Energizer* headlamp line. Featuring LED technology, users get an extraordinarily bright, lightweight hands-free solution with ample run time. Custom optics offer exceptional direct and peripheral vision, making the *Energizer* Vision HD+ Focus a perfect light for home, work and outdoor activities. Featuring patented Digital Focus, users can easily broaden or narrow their field of vision with a simple button press. Memory Recall allows users to quickly access to their favorite focus setting next time the light is activated. With an adjustable head strap, water-resistant design and pivoting head to direct light exactly as needed, *Energizer* continues to deliver innovative lighting solutions.

Lumens	Runtime	Beam Distance	Drop	Water Ingress
<p>FL1 STANDARD 400 LUMENS</p>	<p>FL1 STANDARD 3h</p>	<p>FL1 STANDARD 85m</p>	<p>FL1 STANDARD 1m</p>	<p>FL1 STANDARD IPX4</p>

- ### DESIGN BENEFITS
- ✓ Patented Digital Focus allows users to broaden or narrow the light beam
 - ✓ Red LED mode allows users to preserve night vision
 - ✓ Next Push Off to avoid unnecessary switch cycles
 - ✓ Compact, lightweight design
 - ✓ Water-resistant with shatterproof lens

- ### PERFORMANCE BENEFITS
- ✓ Memory Recall feature permits to access preferred focus setting the next time the light is switched on
 - ✓ Up to 4X brighter than standard LED technology
 - ✓ Custom optics deliver exceptional direct and peripheral vision

- ### LIGHT AND POWER SOURCE
- ✓ Features LED Technology
 - ✓ Operates on 3 AAA Batteries

PRODUCT SPECIFICATIONS

Weight:	53 Grams / 1.9 Ounces
Dimensions:	59 mm x 49 mm x 36 mm 2.3" x 1.9" x 1.4"

ELECTRICAL CHARACTERISTICS

Nominal Power Consumption:	3.45 W
Batteries:	3 AAA Energizer E92 4.5V dc
LED Specifications:	LED 3.0V cc / 1150 mA

DISCLAIMERS

Tested according to ANSI FL1 Standards.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

CERTIFICATES AND COMPLIANCE

EMC, EN62471, FCC	
-------------------	--

Publish Date: 08-06-2022



BATTERY SPECIFICATIONS

Battery Type	Energizer Max Alkaline
Battery Size	AAA
Number of Cells	3

BATTERY PERFORMANCE

Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
High	400	3	85
Low	45	35	30
Full Spot	-	-	-
Full Flood	-	-	-
Red	-	-	-

Modes
High, Low, Full Spot, Full Flood, Red

OPERATING INSTRUCTIONS

1. Press 1 time for Night Vision (red).
2. Press 2 times for high
3. Press 3 times for low.
4. After 2 seconds in a mode, next press will be off.
5. Digital Focus: Press and hold right button on high or low to adjust the amount of spot and flood. Release to set focus setting.
6. Memory Recall: Press right button when light is off to return to last light focus setting.

BATTERY CHANGING INSTRUCTIONS

1. Lift latch to unlock battery door.
2. Open battery door and follow orientation instructions inside battery compartment to replace the batteries.
3. Close and press latch to lock.