



The *Energizer* Vision Ultra HD Headlamp brings outstanding performance in a compact design. The headlamp shows innovative features as the *Energizer* Smart Dimming technology that allow to easily control light intensity. In addition to the white LED, this light has green and red LEDs which enhance night vision for outdoors activities such as hunting and fishing. The VisionGuard technology gradually increases the light intensity to prevent a high beam straight in the users' eyes. The low battery indicator, located in the front of the light, will flash when battery is low, warning consumers that it is almost time to change the batteries. With an adjustable head strap, water-resistant design and pivoting head to direct light exactly as needed, *Energizer* continues to deliver innovative lighting solutions.

Lumens	Runtime	Beam Distance	Drop	Water Ingress

- ### DESIGN BENEFITS
- ✓ *Energizer* Smart Dimming technology to control light intensity
  - ✓ VisionGuard protects vision by gradually increasing light intensity
  - ✓ Next Push Off to avoid unnecessary switch cycles
  - ✓ Low battery indicator
  - ✓ Red and Green LEDs for night vision
  - ✓ Water-resistant with shatterproof lens

- ### PERFORMANCE BENEFITS
- ✓ Up to 15X Brighter than Standard LED Technology
  - ✓ Long Run Time in High and Low modes
  - ✓ 7 modes: High, Low, Wide, Wide Low, Red, Flashing Red, Green

- ### LIGHT AND POWER SOURCE
- ✓ Features LED Technology
  - ✓ Operates on 3 AAA *Energizer* MAX® (Batteries Included)

### PRODUCT SPECIFICATIONS

<b>Weight:</b>	53 Grams / 1.9 Ounces
<b>Dimensions:</b>	59 mm x 49 mm x 37 mm 2.3" x 1.9" x 1.5"

### ELECTRICAL CHARACTERISTICS

<b>Nominal Power Consumption:</b>	4.20 W
<b>Batteries:</b>	3 AAA Energizer E92 4.5V dc
<b>LED Specifications:</b>	LED 3.0V cc / 1400 mA

### DISCLAIMERS

Tested according to ANSI FL1 Standards.  
 This device complies with part 15 of the FCC Rules.  
 Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

### CERTIFICATES AND COMPLIANCE

EMC, EN62471, FCC	
-------------------	--



### BATTERY SPECIFICATIONS

<b>Battery Type</b>	ENR Max Alkaline
<b>Battery Size</b>	AAA
<b>Number of Cells</b>	3

### BATTERY PERFORMANCE

Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
High	450	2h 45m	85
Low	30	50	20
Wide	-	-	-
Wide Low (dim.)	-	-	-
Red	-	-	-
Flashing Red	-	-	-
Green	-	-	-

**Modes**

High, Low, Wide, Wide Low (dim.), Red, Red Flashing, Green
--

Publish Date: 08-06-2022

## OPERATING INSTRUCTIONS

1. Press button with bump to turn on/off.
2. Press 1 time for High (Spot and Wide).
3. Press 2 times for Wide only..
4. Press 3 times for Low (Spot and Wide).
5. Press and hold in any white light mode for dimming. Light will flash at highest and lowest settings. Release to set light level.
6. Press other button for colored modes
7. Press 1 time for Red.
8. Press 2 times for Flashing Red.
9. Press 3 times for Green.
10. After 2 seconds in any mode, next press will be off.

## BATTERY CHANGING INSTRUCTIONS

1. Lift latch to unlock battery door.
2. Open battery door and follow orientation instructions inside battery compartment to replace the batteries.
3. Close and press latch to lock.